

# TECHNICAL DATA

## PCM - TRANSFORMER PCM-FLÜ

<b>Transformer ratio</b>	<b>: 1 : 1</b>
<b>Impedance matching</b>	<b>: 150 : 150 Ohm</b>
<b>Frequency range</b>	<b>: 25 kHz – 2,1 MHz</b>
<b>Transmission loss</b>	<b>: <math>\leq 0,3</math> dB</b>
<b>Unbalance loss</b>	<b>: <math>\geq 22</math> dB</b>
<b>Balanced attenuation</b>	<b>: <math>\geq 52</math> dB (552 kHz)</b>
<b>Copper resistance</b>	<b>: <math>&lt; 0,5</math> Ohm</b>
<b>Test voltage</b>	<b>: 2 kV<sub>eff</sub> / 50 Hz / 10 sec.</b>
<b>Model</b>	<b>: 09</b>
<b>Drawing No.</b>	<b>: WS 40962</b>
<b>Article No.</b>	<b>: 332259</b>

Technical modifications reserved

status: 01/2017