

**TECHNICAL DATA**  
**PCM - TRANSFORMER PCM-FLÜ**  
**FOR TERMINATION OF SYMMETRICAL EARTH RESP. AERIAL CABLES**

<b>Transformer ratio</b>	<b>: 1 : 1</b>	
<b>Impedance matching</b>	<b>: 600 :600 Ohm /</b>	<b>150 : 150 Ohm</b>
<b>Frequency range</b>	<b>: 0,3 - 6 kHz /</b>	<b>6 kHz - 2 MHz</b>
<b>Transmission loss</b>	<b>: <math>\leq 1</math> dB /</b>	<b><math>\leq 0,4</math> dB</b>
<b>Unbalance loss</b>	<b>: -- /</b>	<b>&gt; 20 dB</b>
<b>Balanced attenuation</b>	<b>: &gt; 75 dB (800 Hz) /</b>	<b>&gt; 52 dB (552 kHz)</b>
<b>Copper resistance</b>	<b>: &lt; 0,5 Ohm</b>	
<b>Test voltage</b>	<b>: 10 kV<sub>eff</sub> / 50 Hz / 10 sec.</b>	
<b>Model</b>	<b>: 14</b>	<b>15</b>
<b>Drawing No.</b>	<b>: WS 41448</b>	<b>WS 41548</b>
<b>Article No.</b>	<b>: 331724</b>	<b>330663</b>

Technical modifications reserved

status: 01/2017