

# TECHNICAL DATA

## LOW FREQUENCY TRANSFORMER NFLÜ 327

<b>Transformation ratio</b>	<b>: 1 : 1 / 1 : 2 / 1 : 2,66</b>
<b>Impedance matching:</b>	<b>600:600 / 600:1200 / 600:1600 Ohm</b>
<b>Frequency range:</b>	<b>0,3 - 3,4 kHz</b>
<b>Ringing voltage:</b>	<b>60 V / 25 Hz</b>
<b>Transmission loss</b>	<b>: <math>\leq 0,3</math> dB</b>
<b>Unbalance attenuation</b>	<b>: <math>\geq 26</math> dB</b>
<b>Balanced attenuation</b>	<b>: 85 dB (800 Hz)</b>
<b>Voltage endurance</b>	<b>: 2 kV / 50 Hz / 10 sek.</b>
<b>Model</b>	<b>: 01</b>
<b>Drawing No.</b>	<b>: WS 20134</b>
<b>Article No.</b>	<b>: 314404</b>

Subject to change

Status: 01/2017



EDWANZ group

Product Division Electromechanical Systems