

TECHNICAL DATA

Low-frequency Transformers

Transformer ratio	: 1 : 1	
Impedance matching	: -	
Frequency range	: 0.3 – 3.4 kHz	
Ringling voltage	: 60 V / 25 Hz	
Transmission loss	: ≤ 0.26 dB	
Unbalance loss	: -	
Balanced loss	: ≥ 87 dB (at 800 Hz)	
Voltage endurance	: 2 kV / 50 Hz / 10 sec.	
Model	: 01	03
Drawing No.	: WS 10108	WS 10308
Article No.	: 303313	303314

Technical modifications reserved

Status: 01/2017